




OUTLINE

PIN CONFIGURATION



Pin	Description
1	input
5	+V _B
9	output
2.3.7.8	common

FEATURES ➤

- Excellent linearity
- Extremely low noise
- Excellent return loss properties
- High reliability

► DESCRIPTION

Hybrid amplifier module operating over a frequency range of 5 to 200 MHz at a voltage supply of +24V(DC)

QUICK REFERENCE DATA

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNITS
G _p	power gain	f=10 MHz	35	-	36	dB
I _{tot}	total current consumption(DC)	V _B =24V	140	-	160	mA

LIMITING VALUES

In accordance with the Absolute Maximum Rating System

SYMBOL	PARAMETER	MIN.	MAX.	UNITS
V _i	RF input voltage	-	55	dBmV
T _{stg}	storage temperature	-40	+100	°C
T _{mb}	operating mounting base temperature	-20	+90	°C

CHARACTERISTICS(Bandwidth 5 to 200MHz; $T_{mb}=25^{\circ}\text{C}$, $V_B=24\text{V}$, $Z_S=Z_L=75\Omega$)

PART NUMBER			Egi2003524R			
SYMBOL	PARAMETER	UNIT	MIN.	TYP.	MAX.	CONDITIONS
G_P	power gain	dB	35	-	36	$f=10\text{MHz}$
SL	slope cable equivalent	dB	-0.5	-	0.5	$f=5$ to 200 MHz
FL	flatness of frequency response	dB	-	-	± 0.5	$f=5$ to 200 MHz
S_{11}	input return loss	dB	-	-	-18	$f=5$ to 200 MHz
S_{22}	output return loss	dB	-	-	-18	$f=5$ to 200 MHz
CTB	composite triple beat	dB	-	-	-70	17 channels ; $V_o=50\text{dBmV}$
CSO	composite second order distortion	dB	-	-	-63	CTB measured at 77.25 MHz
X_{mod}	cross modulation	dB	-	-	-62	CSO measured at 78.5 MHz;
V_o	output voltage	dBmV	65	-	-	$d_{im}=-60\text{dB}$
F	noise figure	dB	-	-	4	$f=200\text{ MHz}$
I_{tot}	total current consumption(DC)	mA	140	-	160	$V_B=+24\text{V}$

The module normally operates at $V_B=24\text{V}(\pm 0.5)$ **MODULE DIMENSIONS**